

GENERATING AND DISPLAYING SPATIALLY OFFSET SUB- FRAMES

Cross-Reference to Related Applications

5 This application is related to U.S. Patent Application Serial No.
10/213,555, filed on August 7, 2002, entitled IMAGE DISPLAY SYSTEM
AND METHOD; U.S. Patent Application Serial No. 10/242,195, filed on
September 11, 2002, entitled IMAGE DISPLAY SYSTEM AND METHOD;
and U.S. Patent Application Serial No. 10/242,545, filed on September 11, 2002,
10 entitled IMAGE DISPLAY SYSTEM AND METHOD. Each of the above U.S.
Patent Applications is assigned to the assignee of the present invention, and is
hereby incorporated by reference herein.

The Field of the Invention

15 The present invention generally relates to display systems, and more
particularly to generating and displaying spatially offset sub-frames.

Background of the Invention

20 A conventional system or device for displaying an image, such as a
display, projector, or other imaging system, produces a displayed image by
addressing an array of individual picture elements or pixels arranged in
horizontal rows and vertical columns. A resolution of the displayed image is
defined as the number of horizontal rows and vertical columns of individual
pixels forming the displayed image. The resolution of the displayed image is
25 affected by a resolution of the display device itself as well as a resolution of the
image data processed by the display device and used to produce the displayed
image.

Typically, to increase a resolution of the displayed image, the resolution
of the display device as well as the resolution of the image data used to produce
30 the displayed image must be increased. Increasing a resolution of the display
device, however, increases a cost and complexity of the display device. In

addition, higher resolution image data may not be available and/or may be difficult to generate.

Summary of the Invention

5 One form of the present invention provides a method of displaying an image with a display device. The method includes receiving image data for the image. A first sub-frame and a second sub-frame are generated based on combinations of pixel values from the image data. The method includes alternating between displaying the first sub-frame in a first position and
10 displaying the second sub-frame in a second position spatially offset from the first position.

Brief Description of the Drawings

Figure 1 is a block diagram illustrating an image display system
15 according to one embodiment of the present invention.

Figures 2A-2C are schematic diagrams illustrating the display of two sub-frames according to one embodiment of the present invention.

Figures 3A-3E are schematic diagrams illustrating the display of four sub-frames according to one embodiment of the present invention.

20 Figures 4A-4E are schematic diagrams illustrating the display of a pixel with an image display system according to one embodiment of the present invention.

Figure 5 is a diagram illustrating the generation of low resolution sub-frames from an original high resolution image using a nearest neighbor
25 algorithm according to one embodiment of the present invention.

Figure 6 is a diagram illustrating the generation of low resolution sub-frames from an original high resolution image using a bilinear algorithm according to one embodiment of the present invention.

Figure 7 is a block diagram illustrating a system for generating a
30 simulated high resolution image according to one embodiment of the present invention.

Figure 8 is a block diagram illustrating a system for generating a simulated high resolution image for two-position processing based on separable upsampling according to one embodiment of the present invention.

5 Figure 9 is a block diagram illustrating a system for generating a simulated high resolution image for two-position processing based on non-separable upsampling according to one embodiment of the present invention.

Figure 10 is a block diagram illustrating a system for generating a simulated high resolution image for four-position processing according to one embodiment of the present invention.

10 Figure 11 is a block diagram illustrating the comparison of a simulated high resolution image and a desired high resolution image according to one embodiment of the present invention.

Figure 12 is a diagram illustrating the effect in the frequency domain of the upsampling of a sub-frame according to one embodiment of the present
15 invention.

Figure 13 is a diagram illustrating the effect in the frequency domain of the shifting of an upsampled sub-frame according to one embodiment of the present invention.

20 Figure 14 is a diagram illustrating regions of influence for pixels in an upsampled image according to one embodiment of the present invention.

Figure 15 is a diagram illustrating the generation of an initial simulated high resolution image based on an adaptive multi-pass algorithm according to one embodiment of the present invention.

25 Figure 16 is a diagram illustrating the generation of correction data based on an adaptive multi-pass algorithm according to one embodiment of the present invention.

Figure 17 is a diagram illustrating the generation of updated sub-frames based on an adaptive multi-pass algorithm according to one embodiment of the present invention.

Figure 18 is a diagram illustrating the generation of correction data based on an adaptive multi-pass algorithm according to another embodiment of the present invention.

5

Description of the Preferred Embodiments

In the following detailed description of the preferred embodiments, reference is made to the accompanying drawings, which form a part hereof, and in which is shown by way of illustration specific embodiments in which the invention may be practiced. It is to be understood that other embodiments may
10 be utilized and structural or logical changes may be made without departing from the scope of the present invention. The following detailed description, therefore, is not to be taken in a limiting sense, and the scope of the present invention is defined by the appended claims.

15

I. Spatial and Temporal Shifting of Sub-frames

Some display systems, such as some digital light projectors, may not have sufficient resolution to display some high resolution images. Such systems can be configured to give the appearance to the human eye of higher resolution images by displaying spatially and temporally shifted lower resolution images.
20 The lower resolution images are referred to as sub-frames. A problem of sub-frame generation, which is addressed by embodiments of the present invention, is to determine appropriate values for the sub-frames so that the displayed sub-frames are close in appearance to how the high-resolution image from which the sub-frames were derived would appear if directly displayed.

25

One embodiment of a display system that provides the appearance of enhanced resolution through temporal and spatial shifting of sub-frames is described in the above-cited U.S. patent applications, and is summarized below with reference to Figures 1-4E.

Figure 1 is a block diagram illustrating an image display system 10
30 according to one embodiment of the present invention. Image display system 10 facilitates processing of an image 12 to create a displayed image 14. Image 12 is

defined to include any pictorial, graphical, and/or textural characters, symbols, illustrations, and/or other representation of information. Image 12 is represented, for example, by image data 16. Image data 16 includes individual picture elements or pixels of image 12. While one image is illustrated and described as being processed by image display system 10, it is understood that a plurality or series of images may be processed and displayed by image display system 10.

In one embodiment, image display system 10 includes a frame rate conversion unit 20 and an image frame buffer 22, an image processing unit 24, and a display device 26. As described below, frame rate conversion unit 20 and image frame buffer 22 receive and buffer image data 16 for image 12 to create an image frame 28 for image 12. Image processing unit 24 processes image frame 28 to define one or more image sub-frames 30 for image frame 28, and display device 26 temporally and spatially displays image sub-frames 30 to produce displayed image 14.

Image display system 10, including frame rate conversion unit 20 and/or image processing unit 24, includes hardware, software, firmware, or a combination of these. In one embodiment, one or more components of image display system 10, including frame rate conversion unit 20 and/or image processing unit 24, are included in a computer, computer server, or other microprocessor-based system capable of performing a sequence of logic operations. In addition, processing can be distributed throughout the system with individual portions being implemented in separate system components.

Image data 16 may include digital image data 161 or analog image data 162. To process analog image data 162, image display system 10 includes an analog-to-digital (A/D) converter 32. As such, A/D converter 32 converts analog image data 162 to digital form for subsequent processing. Thus, image display system 10 may receive and process digital image data 161 and/or analog image data 162 for image 12.

Frame rate conversion unit 20 receives image data 16 for image 12 and buffers or stores image data 16 in image frame buffer 22. More specifically,

frame rate conversion unit 20 receives image data 16 representing individual lines or fields of image 12 and buffers image data 16 in image frame buffer 22 to create image frame 28 for image 12. Image frame buffer 22 buffers image data 16 by receiving and storing all of the image data for image frame 28, and frame
5 rate conversion unit 20 creates image frame 28 by subsequently retrieving or extracting all of the image data for image frame 28 from image frame buffer 22. As such, image frame 28 is defined to include a plurality of individual lines or fields of image data 16 representing an entirety of image 12. Thus, image frame 28 includes a plurality of columns and a plurality of rows of individual pixels
10 representing image 12.

Frame rate conversion unit 20 and image frame buffer 22 can receive and process image data 16 as progressive image data and/or interlaced image data. With progressive image data, frame rate conversion unit 20 and image frame buffer 22 receive and store sequential fields of image data 16 for image 12.
15 Thus, frame rate conversion unit 20 creates image frame 28 by retrieving the sequential fields of image data 16 for image 12. With interlaced image data, frame rate conversion unit 20 and image frame buffer 22 receive and store odd fields and even fields of image data 16 for image 12. For example, all of the odd fields of image data 16 are received and stored and all of the even fields of
20 image data 16 are received and stored. As such, frame rate conversion unit 20 de-interlaces image data 16 and creates image frame 28 by retrieving the odd and even fields of image data 16 for image 12.

Image frame buffer 22 includes memory for storing image data 16 for one or more image frames 28 of respective images 12. Thus, image frame buffer
25 22 constitutes a database of one or more image frames 28. Examples of image frame buffer 22 include non-volatile memory (e.g., a hard disk drive or other persistent storage device) and may include volatile memory (e.g., random access memory (RAM)).

By receiving image data 16 at frame rate conversion unit 20 and
30 buffering image data 16 with image frame buffer 22, input timing of image data 16 can be decoupled from a timing requirement of display device 26. More

specifically, since image data 16 for image frame 28 is received and stored by image frame buffer 22, image data 16 can be received as input at any rate. As such, the frame rate of image frame 28 can be converted to the timing requirement of display device 26. Thus, image data 16 for image frame 28 can
5 be extracted from image frame buffer 22 at a frame rate of display device 26.

In one embodiment, image processing unit 24 includes a resolution adjustment unit 34 and a sub-frame generation unit 36. As described below, resolution adjustment unit 34 receives image data 16 for image frame 28 and adjusts a resolution of image data 16 for display on display device 26, and sub-
10 frame generation unit 36 generates a plurality of image sub-frames 30 for image frame 28. More specifically, image processing unit 24 receives image data 16 for image frame 28 at an original resolution and processes image data 16 to increase, decrease, and/or leave unaltered the resolution of image data 16. Accordingly, with image processing unit 24, image display system 10 can
15 receive and display image data 16 of varying resolutions.

Sub-frame generation unit 36 receives and processes image data 16 for image frame 28 to define a plurality of image sub-frames 30 for image frame 28. If resolution adjustment unit 34 has adjusted the resolution of image data 16, sub-frame generation unit 36 receives image data 16 at the adjusted resolution.
20 The adjusted resolution of image data 16 may be increased, decreased, or the same as the original resolution of image data 16 for image frame 28. Sub-frame generation unit 36 generates image sub-frames 30 with a resolution which matches the resolution of display device 26. Image sub-frames 30 are each of an area equal to image frame 28. Sub-frames 30 each include a plurality of
25 columns and a plurality of rows of individual pixels representing a subset of image data 16 of image 12, and have a resolution that matches the resolution of display device 26.

Each image sub-frame 30 includes a matrix or array of pixels for image frame 28. Image sub-frames 30 are spatially offset from each other such that
30 each image sub-frame 30 includes different pixels and/or portions of pixels. As

such, image sub-frames 30 are offset from each other by a vertical distance and/or a horizontal distance, as described below.

Display device 26 receives image sub-frames 30 from image processing unit 24 and sequentially displays image sub-frames 30 to create displayed image 14. More specifically, as image sub-frames 30 are spatially offset from each other, display device 26 displays image sub-frames 30 in different positions according to the spatial offset of image sub-frames 30, as described below. As such, display device 26 alternates between displaying image sub-frames 30 for image frame 28 to create displayed image 14. Accordingly, display device 26 displays an entire sub-frame 30 for image frame 28 at one time.

In one embodiment, display device 26 performs one cycle of displaying image sub-frames 30 for each image frame 28. Display device 26 displays image sub-frames 30 so as to be spatially and temporally offset from each other. In one embodiment, display device 26 optically steers image sub-frames 30 to create displayed image 14. As such, individual pixels of display device 26 are addressed to multiple locations.

In one embodiment, display device 26 includes an image shifter 38. Image shifter 38 spatially alters or offsets the position of image sub-frames 30 as displayed by display device 26. More specifically, image shifter 38 varies the position of display of image sub-frames 30, as described below, to produce displayed image 14.

In one embodiment, display device 26 includes a light modulator for modulation of incident light. The light modulator includes, for example, a plurality of micro-mirror devices arranged to form an array of micro-mirror devices. As such, each micro-mirror device constitutes one cell or pixel of display device 26. Display device 26 may form part of a display, projector, or other imaging system.

In one embodiment, image display system 10 includes a timing generator 40. Timing generator 40 communicates, for example, with frame rate conversion unit 20, image processing unit 24, including resolution adjustment unit 34 and sub-frame generation unit 36, and display device 26, including image

shifter 38. As such, timing generator 40 synchronizes buffering and conversion of image data 16 to create image frame 28, processing of image frame 28 to adjust the resolution of image data 16 and generate image sub-frames 30, and positioning and displaying of image sub-frames 30 to produce displayed image 14. Accordingly, timing generator 40 controls timing of image display system 10 such that entire sub-frames of image 12 are temporally and spatially displayed by display device 26 as displayed image 14.

In one embodiment, as illustrated in Figures 2A and 2B, image processing unit 24 defines two image sub-frames 30 for image frame 28. More specifically, image processing unit 24 defines a first sub-frame 301 and a second sub-frame 302 for image frame 28. As such, first sub-frame 301 and second sub-frame 302 each include a plurality of columns and a plurality of rows of individual pixels 18 of image data 16. Thus, first sub-frame 301 and second sub-frame 302 each constitute an image data array or pixel matrix of a subset of image data 16.

In one embodiment, as illustrated in Figure 2B, second sub-frame 302 is offset from first sub-frame 301 by a vertical distance 50 and a horizontal distance 52. As such, second sub-frame 302 is spatially offset from first sub-frame 301 by a predetermined distance. In one illustrative embodiment, vertical distance 50 and horizontal distance 52 are each approximately one-half of one pixel.

As illustrated in Figure 2C, display device 26 alternates between displaying first sub-frame 301 in a first position and displaying second sub-frame 302 in a second position spatially offset from the first position. More specifically, display device 26 shifts display of second sub-frame 302 relative to display of first sub-frame 301 by vertical distance 50 and horizontal distance 52. As such, pixels of first sub-frame 301 overlap pixels of second sub-frame 302. In one embodiment, display device 26 performs one cycle of displaying first sub-frame 301 in the first position and displaying second sub-frame 302 in the second position for image frame 28. Thus, second sub-frame 302 is spatially and temporally displayed relative to first sub-frame 301. The display of two

temporally and spatially shifted sub-frames in this manner is referred to herein as two-position processing.

In another embodiment, as illustrated in Figures 3A-3D, image processing unit 24 defines four image sub-frames 30 for image frame 28. More specifically, image processing unit 24 defines a first sub-frame 301, a second sub-frame 302, a third sub-frame 303, and a fourth sub-frame 304 for image frame 28. As such, first sub-frame 301, second sub-frame 302, third sub-frame 303, and fourth sub-frame 304 each include a plurality of columns and a plurality of rows of individual pixels 18 of image data 16.

In one embodiment, as illustrated in Figures 3B-3D, second sub-frame 302 is offset from first sub-frame 301 by a vertical distance 50 and a horizontal distance 52, third sub-frame 303 is offset from first sub-frame 301 by a horizontal distance 54, and fourth sub-frame 304 is offset from first sub-frame 301 by a vertical distance 56. As such, second sub-frame 302, third sub-frame 303, and fourth sub-frame 304 are each spatially offset from each other and spatially offset from first sub-frame 301 by a predetermined distance. In one illustrative embodiment, vertical distance 50, horizontal distance 52, horizontal distance 54, and vertical distance 56 are each approximately one-half of one pixel.

As illustrated schematically in Figure 3E, display device 26 alternates between displaying first sub-frame 301 in a first position P_1 , displaying second sub-frame 302 in a second position P_2 spatially offset from the first position, displaying third sub-frame 303 in a third position P_3 spatially offset from the first position, and displaying fourth sub-frame 304 in a fourth position P_4 spatially offset from the first position. More specifically, display device 26 shifts display of second sub-frame 302, third sub-frame 303, and fourth sub-frame 304 relative to first sub-frame 301 by the respective predetermined distance. As such, pixels of first sub-frame 301, second sub-frame 302, third sub-frame 303, and fourth sub-frame 304 overlap each other.

In one embodiment, display device 26 performs one cycle of displaying first sub-frame 301 in the first position, displaying second sub-frame 302 in the

second position, displaying third sub-frame 303 in the third position, and displaying fourth sub-frame 304 in the fourth position for image frame 28.

Thus, second sub-frame 302, third sub-frame 303, and fourth sub-frame 304 are spatially and temporally displayed relative to each other and relative to first sub-frame 301. The display of four temporally and spatially shifted sub-frames in this manner is referred to herein as four-position processing.

Figures 4A-4E illustrate one embodiment of completing one cycle of displaying a pixel 181 from first sub-frame 301 in the first position, displaying a pixel 182 from second sub-frame 302 in the second position, displaying a pixel 183 from third sub-frame 303 in the third position, and displaying a pixel 184 from fourth sub-frame 304 in the fourth position. More specifically, Figure 4A illustrates display of pixel 181 from first sub-frame 301 in the first position, Figure 4B illustrates display of pixel 182 from second sub-frame 302 in the second position (with the first position being illustrated by dashed lines), Figure 4C illustrates display of pixel 183 from third sub-frame 303 in the third position (with the first position and the second position being illustrated by dashed lines), Figure 4D illustrates display of pixel 184 from fourth sub-frame 304 in the fourth position (with the first position, the second position, and the third position being illustrated by dashed lines), and Figure 4E illustrates display of pixel 181 from first sub-frame 301 in the first position (with the second position, the third position, and the fourth position being illustrated by dashed lines).

Sub-frame generation unit 36 (Figure 1) generates sub-frames 30 based on image data in image frame 28. It will be understood by a person of ordinary skill in the art that functions performed by sub-frame generation unit 36 may be implemented in hardware, software, firmware, or any combination thereof. The implementation may be via a microprocessor, programmable logic device, or state machine. Components of the present invention may reside in software on one or more computer-readable mediums. The term computer-readable medium as used herein is defined to include any kind of memory, volatile or non-volatile, such as floppy disks, hard disks, CD-ROMs, flash memory, read-only memory (ROM), and random access memory.

In one form of the invention, sub-frames 30 have a lower resolution than image frame 28. Thus, sub-frames 30 are also referred to herein as low resolution images 30, and image frame 28 is also referred to herein as a high resolution image 28. It will be understood by persons of ordinary skill in the art that the terms low resolution and high resolution are used herein in a comparative fashion, and are not limited to any particular minimum or maximum number of pixels. In one embodiment, sub-frame generation unit 36 is configured to generate sub-frames 30 based on one of five algorithms. These five algorithms are referred to herein as the following: (1) nearest neighbor; (2) bilinear; (3) spatial domain; (4) frequency domain; and (5) adaptive multi-pass.

The nearest neighbor algorithm and the bilinear algorithm according to one form of the invention generate sub-frames 30 by combining pixels from a high resolution image 28. The spatial domain algorithm and the frequency domain algorithm according to one form of the invention generate sub-frames 30 based on the minimization of a global error metric that represents a difference between a simulated high resolution image and a desired high resolution image 28. The adaptive multi-pass algorithm according to one form of the invention generates sub-frames 30 based on the minimization of a local error metric. In one embodiment, sub-frame generation unit 36 includes memory for storing a relationship between sub-frame values and high resolution image values, wherein the relationship is based on minimization of an error metric between the high resolution image values and a simulated high resolution image that is a function of the sub-frame values. Embodiments of each of these five algorithms are described below with reference to Figures 5-18.

25

II. Nearest Neighbor

Figure 5 is a diagram illustrating the generation of low resolution sub-frames 30A and 30B (collectively referred to as sub-frames 30) from an original high resolution image 28 using a nearest neighbor algorithm according to one embodiment of the present invention. In the illustrated embodiment, high resolution image 28 includes four columns and four rows of pixels, for a total of

30

sixteen pixels H1-H16. In one embodiment of the nearest neighbor algorithm, a first sub-frame 30A is generated by taking every other pixel in a first row of the high resolution image 28, skipping the second row of the high resolution image 28, taking every other pixel in the third row of the high resolution image 28, and repeating this process throughout the high resolution image 28. Thus, as shown in Figure 5, the first row of sub-frame 30A includes pixels H1 and H3, and the second row of sub-frame 30A includes pixels H9 and H11. In one form of the invention, a second sub-frame 30B is generated in the same manner as the first sub-frame 30A, but the process begins at a pixel H6 that is shifted down one row and over one column from the first pixel H1. Thus, as shown in Figure 5, the first row of sub-frame 30B includes pixels H6 and H8, and the second row of sub-frame 30B includes pixels H14 and H16.

In one embodiment, the nearest neighbor algorithm is implemented with a 2x2 filter with three filter coefficients of "0" and a fourth filter coefficient of "1" to generate a weighted sum of the pixel values from the high resolution image. Displaying sub-frames 30A and 30B using two-position processing as described above gives the appearance of a higher resolution image. The nearest neighbor algorithm is also applicable to four-position processing, and is not limited to images having the number of pixels shown in Figure 5.

III. Bilinear

Figure 6 is a diagram illustrating the generation of low resolution sub-frames 30C and 30D (collectively referred to as sub-frames 30) from an original high resolution image 28 using a bilinear algorithm according to one embodiment of the present invention. In the illustrated embodiment, high resolution image 28 includes four columns and four rows of pixels, for a total of sixteen pixels H1-H16. Sub-frame 30C includes two columns and two rows of pixels, for a total of four pixels L1-L4. And sub-frame 30D includes two columns and two rows of pixels, for a total of four pixels L5-L8.

In one embodiment, the values for pixels L1-L8 in sub-frames 30C and 30D are generated from the pixel values H1-H16 of image 28 based on the following Equations I-VIII:

Equation I

5
$$L1 = (4H1 + 2H2 + 2H5) / 8$$

Equation II

$$L2 = (4H3 + 2H4 + 2H7) / 8$$

Equation III

$$L3 = (4H9 + 2H10 + 2H13) / 8$$

10 Equation IV

$$L4 = (4H11 + 2H12 + 2H15) / 8$$

Equation V

$$L5 = (4H6 + 2H2 + 2H5) / 8$$

Equation VI

15
$$L6 = (4H8 + 2H4 + 2H7) / 8$$

Equation VII

$$L7 = (4H14 + 2H10 + 2H13) / 8$$

Equation VIII

$$L8 = (4H16 + 2H12 + 2H15) / 8$$

20 As can be seen from the above Equations I-VIII, the values of the pixels L1-L4 in sub-frame 30C are influenced the most by the values of pixels H1, H3, H9, and H11, respectively, due to the multiplication by four. But the values for the pixels L1-L4 in sub-frame 30C are also influenced by the values of diagonal neighbors of pixels H1, H3, H9, and H11. Similarly, the values of the pixels L5-L8 in sub-frame 30D are influenced the most by the values of pixels H6, H8, H14, and H16, respectively, due to the multiplication by four. But the values for the pixels L5-L8 in sub-frame 30D are also influenced by the values of diagonal neighbors of pixels H6, H8, H14, and H16.

30 In one embodiment, the bilinear algorithm is implemented with a 2x2 filter with one filter coefficient of "0" and three filter coefficients having a non-zero value (e.g., 4, 2, and 2) to generate a weighted sum of the pixel values from

the high resolution image. In another embodiment, other values are used for the filter coefficients. Displaying sub-frames 30C and 30D using two-position processing as described above gives the appearance of a higher resolution image. The bilinear algorithm is also applicable to four-position processing, and is not
5 limited to images having the number of pixels shown in Figure 6.

In one form of the nearest neighbor and bilinear algorithms, sub-frames 30 are generated based on a linear combination of pixel values from an original high resolution image as described above. In another embodiment, sub-frames 30 are generated based on a non-linear combination of pixel values from an
10 original high resolution image. For example, if the original high resolution image is gamma-corrected, appropriate non-linear combinations are used in one embodiment to undo the effect of the gamma curve.

IV. Systems for Generating Simulated High Resolution Images

15 Figures 7-10 illustrate systems for generating simulated high resolution images. Based on these systems, spatial domain, frequency domain, and adaptive multi-pass algorithms for generating sub-frames are developed, as described in further detail below.

Figure 7 is a block diagram illustrating a system 400 for generating a
20 simulated high resolution image 412 from two 4x4 pixel low resolution sub-frames 30E according to one embodiment of the present invention. System 400 includes upsampling stage 402, shifting stage 404, convolution stage 406, and summation stage 410. Sub-frames 30E are upsampled by upsampling stage 402 based on a sampling matrix, \mathbf{M} , thereby generating upsampled images. The
25 upsampled images are shifted by shifting stage 404 based on a spatial shifting matrix, \mathbf{S} , thereby generating shifted upsampled images. The shifted upsampled images are convolved with an interpolating filter at convolution stage 406, thereby generating blocked images 408. In the illustrated embodiment, the interpolating filter is a 2x2 filter with filter coefficients of "1", and with the
30 center of the convolution being the upper left position in the 2x2 matrix. The interpolating filter simulates the superposition of low resolution sub-frames on a

high resolution grid. The low resolution sub-frame pixel data is expanded so that the sub-frames can be represented on a high resolution grid. The interpolating filter fills in the missing pixel data produced by upsampling. The blocked images 408 are weighted and summed by summation block 410 to
5 generate the 8x8 pixel simulated high resolution image 412.

Figure 8 is a block diagram illustrating a system 500 for generating a simulated high resolution image 512 for two-position processing based on separable upsampling of two 4x4 pixel low resolution sub-frames 30F and 30G according to one embodiment of the present invention. System 500 includes
10 upsampling stages 502 and 514, shifting stage 518, convolution stages 506 and 522, summation stage 508, and multiplication stage 510. Sub-frame 30F is upsampled by a factor of two by upsampling stage 502, thereby generating an 8x8 pixel upsampled image 504. The dark pixels in upsampled image 504 represent the sixteen pixels from sub-frame 30F, and the light pixels in
15 upsampled image 504 represent zero values. Sub-frame 30G is upsampled by a factor of two by upsampling stage 514, thereby generating an 8x8 pixel upsampled image 516. The dark pixels in upsampled image 516 represent the sixteen pixels from sub-frame 30G, and the light pixels in upsampled image 516 represent zero values. In one embodiment, upsampling stages 502 and 514
20 upsample sub-frames 30F and 30G, respectively, using a diagonal sampling matrix.

The upsampled image 516 is shifted by shifting stage 518 based on a spatial shifting matrix, S , thereby generating shifted upsampled image 520. In the illustrated embodiment, shifting stage 518 performs a one pixel diagonal
25 shift. Images 504 and 520 are convolved with an interpolating filter at convolution stages 506 and 522, respectively, thereby generating blocked images. In the illustrated embodiment, the interpolating filter at convolution stages 506 and 522 is a 2x2 filter with filter coefficients of "1", and with the center of the convolution being the upper left position in the 2x2 matrix. The
30 blocked images generated at convolution stages 506 and 522 are summed by summation block 508, and multiplied by a factor of 0.5 at multiplication stage

510, to generate the 8x8 pixel simulated high resolution image 512. The image data is multiplied by a factor of 0.5 at multiplication stage 510 because, in one embodiment, each of the sub-frames 30F and 30G is displayed for only half of the time slot per period allotted to a color. In another embodiment, rather than
5 multiplying by a factor of 0.5 at multiplication stage 510, the filter coefficients of the interpolating filter at stages 506 and 522 are reduced by a factor of 0.5.

In one embodiment, as shown in Figure 8 and described above, the low resolution sub-frame data is represented by two separate sub-frames 30F and 30G, which are separately upsampled based on a diagonal sampling matrix (i.e.,
10 separable upsampling). In another embodiment, as described below with reference to Figure 9, the low resolution sub-frame data is represented by a single sub-frame, which is upsampled based on a non-diagonal sampling matrix (i.e., non-separable upsampling).

Figure 9 is a block diagram illustrating a system 600 for generating a
15 simulated high resolution image 610 for two-position processing based on non-separable upsampling of an 8x4 pixel low resolution sub-frame 30H according to one embodiment of the present invention. System 600 includes quincunx upsampling stage 602, convolution stage 606, and multiplication stage 608. Sub-frame 30H is upsampled by quincunx upsampling stage 602 based on a
20 quincunx sampling matrix, Q , thereby generating upsampled image 604. The dark pixels in upsampled image 604 represent the thirty-two pixels from sub-frame 30H, and the light pixels in upsampled image 604 represent zero values. Sub-frame 30H includes pixel data for two 4x4 pixel sub-frames for two-position processing. The dark pixels in the first, third, fifth, and seventh rows of
25 upsampled image 604 represent pixels for a first 4x4 pixel sub-frame, and the dark pixels in the second, fourth, sixth, and eighth rows of upsampled image 604 represent pixels for a second 4x4 pixel sub-frame.

The upsampled image 604 is convolved with an interpolating filter at convolution stage 606, thereby generating a blocked image. In the illustrated
30 embodiment, the interpolating filter is a 2x2 filter with filter coefficients of "1", and with the center of the convolution being the upper left position in the 2x2

matrix. The blocked image generated by convolution stage 606 is multiplied by a factor of 0.5 at multiplication stage 608, to generate the 8x8 pixel simulated high resolution image 610.

Figure 10 is a block diagram illustrating a system 700 for generating a simulated high resolution image 706 for four-position processing based on sub-frame 30I according to one embodiment of the present invention. In the embodiment illustrated in Figure 10, sub-frame 30I is an 8x8 array of pixels. Sub-frame 30I includes pixel data for four 4x4 pixel sub-frames for four-position processing. Pixels A1-A16 represent pixels for a first 4x4 pixel sub-frame, pixels B1-B16 represent pixels for a second 4x4 pixel sub-frame, pixels C1-C16 represent pixels for a third 4x4 pixel sub-frame, and pixels D1-D16 represent pixels for a fourth 4x4 pixel sub-frame.

The sub-frame 30I is convolved with an interpolating filter at convolution stage 702, thereby generating a blocked image. In the illustrated embodiment, the interpolating filter is a 2x2 filter with filter coefficients of “1”, and with the center of the convolution being the upper left position in the 2x2 matrix. The blocked image generated by convolution stage 702 is multiplied by a factor of 0.25 at multiplication stage 704, to generate the 8x8 pixel simulated high resolution image 706. The image data is multiplied by a factor of 0.25 at multiplication stage 704 because, in one embodiment, each of the four sub-frames represented by sub-frame 30I is displayed for only one fourth of the time slot per period allotted to a color. In another embodiment, rather than multiplying by a factor of 0.25 at multiplication stage 704, the filter coefficients of the interpolating filter are correspondingly reduced.

25

V. Generation of Sub-frames Based on Error Minimization

As described above, systems 400, 500, 600, and 700 generate simulated high resolution images 412, 512, 610, and 706, respectively, based on low resolution sub-frames. If the sub-frames are optimal, the simulated high resolution image will be as close as possible to the original high resolution image 28. Various error metrics may be used to determine how close a

30

simulated high resolution image is to an original high resolution image, including mean square error, weighted mean square error, as well as others.

Figure 11 is a block diagram illustrating the comparison of a simulated high resolution image 412/512/610/706 and a desired high resolution image 28 according to one embodiment of the present invention. A simulated high resolution image 412, 512, 610, or 706, is subtracted on a pixel-by-pixel basis from high resolution image 28 at subtraction stage 802. In one embodiment, the resulting error image data is filtered by a human visual system (HVS) weighting filter (W) 804. In one form of the invention, HVS weighting filter 804 filters the error image data based on characteristics of the human visual system. In one embodiment, HVS weighting filter 804 reduces or eliminates high frequency errors. The mean squared error of the filtered data is then determined at stage 806 to provide a measure of how close the simulated high resolution image 412, 512, 610, or 706 is to the desired high resolution image 28.

In one embodiment, systems 400, 500, 600, and 700 are represented mathematically in an error cost equation that measures the difference between a simulated high resolution image 412, 512, 610, or 706, and the original high resolution image 28. Optimal sub-frames are identified by solving the error cost equation for the sub-frame data that provides the minimum error between the simulated high resolution image and the desired high resolution image. In one embodiment, globally optimum solutions are obtained in the spatial domain and in the frequency domain, and a locally optimum solution is obtained using an adaptive multi-pass algorithm. The spatial domain, frequency domain, and adaptive multi-pass algorithms are described in further detail below with reference to Figures 12-18.

VI. Spatial Domain

A spatial domain solution for generating optimal sub-frames according to one embodiment is described in the context of the system 600 shown in Figure 9. The system 600 shown in Figure 9 can be represented mathematically in an error cost function by the following Equation IX:

Equation IX

$$l_Q^* = \underset{l_Q}{\operatorname{argmin}} J = \underset{l_Q}{\operatorname{argmin}} \sum_{\mathbf{n}} \left(\sum_{\mathbf{k}} l_Q(\mathbf{k}) f(\mathbf{n} - \mathbf{k}) - h(\mathbf{n}) \right)^2$$

where:

l_Q^* = optimal low resolution data for sub-frame
30H;

J = error cost function to be minimized;

\mathbf{n} and \mathbf{k} = indices for identifying high resolution
pixel locations for images 604 and 610;

$l_Q(\mathbf{k})$ = image data from upsampled image 604 at
location \mathbf{k} ;

$f(\mathbf{n} - \mathbf{k})$ = filter coefficient of the interpolating
filter at a position $\mathbf{n} - \mathbf{k}$; and

$h(\mathbf{n})$ = image data for desired high resolution
image 28 at location \mathbf{n} .

The summation of " $l_Q(\mathbf{k}) f(\mathbf{n} - \mathbf{k})$ " in Equation IX represents the
convolution of the upsampled image 604 and the interpolating filter, f , performed
at stage 606 in system 600. The filter operation is performed by essentially
sliding the lower right pixel of the 2x2 interpolating filter over each pixel of the
upsampled image 604. The four pixels of the upsampled image 604 within the
2x2 interpolating filter window are multiplied by the corresponding filter
coefficient (i.e., "1" in the illustrated embodiment). The results of the four
multiplications are summed, and the value for the pixel of the upsampled image
604 corresponding to the lower right position of the interpolating filter is
replaced by the sum of the four multiplication results. The high resolution data,
 $h(\mathbf{n})$, from the high resolution image 28 is subtracted from the convolution value,
 $l_Q(\mathbf{k}) f(\mathbf{n} - \mathbf{k})$, to provide an error value. The summation of the squared error
over all of the high resolution pixel locations provides a measure of the error to
be minimized.

An optimal spatial domain solution can be obtained by taking the derivative of Equation IX with respect to each of the low resolution pixels, and setting it equal to zero as shown in the following Equation X:

Equation X

$$\frac{\partial J}{\partial l_Q^*(t)} = 0, \quad t \in \Theta$$

5

where:

Θ = the set of quincunx lattice points.

Thus, as can be seen from Equation X, the derivative is taken only at the set of quincunx lattice points, which correspond to the dark pixels in upsampled image 604 in Figure 9. Inserting the equation for J given in Equation IX into Equation X, and taking the derivative as specified in Equation X, results in the following Equation XI:

10

Equation XI

$$\sum_k l_Q^*(k) C_{ff}(t - k) = \sum_n h(n) f(n - t), \quad t \in \Theta$$

The symbol, C_{ff} , in Equation XI represents the auto-correlation coefficients of the interpolating filter, f , as defined by the following Equation XII:

15

Equation XII

$$C_{ff}(n) = \sum_k f(n) f(n + k)$$

Equation XI can be put into vector form as shown in the following Equation XIII:

20

Equation XIII

$$C_{ff} l_Q^* = h_f, \quad t \in \Theta$$

where:

C_{ff} = matrix of auto-correlation coefficients of the

interpolating filter, f .

\mathbf{l}_Q^* = vector representing the unknown image data for sub-frame 30H, as well as “don’t care” data (i.e., the image data corresponding to the light pixels in upsampled image 604);

\mathbf{h}_f = vector representing a filtered version of the simulated high resolution image 610 using the interpolating filter, f .

10 Deleting the rows and columns corresponding to “don’t care” data (i.e., the data that is not in the set of quincunx lattice points, Θ), results in the following Equation XIV:

Equation XIV

$$\tilde{\mathbf{C}}_{ff} \tilde{\mathbf{l}}_Q^* = \tilde{\mathbf{h}}_f$$

where:

$\tilde{\mathbf{l}}_Q^*$ = vector representing only the unknown image data for sub - frame 30H.

15 The above Equation XIV is a sparse non-Toeplitz system representing a sparse system of linear equations. Since the matrix of auto-correlation coefficients is known, and the vector representing the filtered version of the simulated high resolution image 610 is known, Equation XIV can be solved to
20 determine the optimal image data for sub-frame 30H. In one embodiment, sub-frame generation unit 36 is configured to solve Equation XIV to generate sub-frames 30.

VII. Frequency Domain

25 A frequency domain solution for generating optimal sub-frames 30 according to one embodiment is described in the context of the system 500 shown in Figure 8. Before describing the frequency domain solution, a few

properties of the fast fourier transform (FFT) that are applicable to the frequency domain solution are described with reference to Figures 12 and 13.

Figure 12 is a diagram illustrating the effect in the frequency domain of the upsampling of a 4x4 pixel sub-frame 30J according to one embodiment of the present invention. As shown in Figure 12, sub-frame 30J is upsampled by a factor of two by upsampling stage 902 to generate an 8x8 pixel upsampled image 904. The dark pixels in upsampled image 904 represent the sixteen pixels from sub-frame 30J, and the light pixels in upsampled image 904 represent zero values. Taking the FFT of sub-frame 30J results in image (L) 906. Taking the FFT of upsampled image 904 results in image (L_U) 908. Image (L_U) 908 includes four 4x4 pixel portions, which are image portion (L_1) 910A, image portion (L_2) 910B, image portion (L_3) 910C, and image portion (L_4) 910D. As shown in Figure 12, image portions 910A-910D are each the same as image 906 (i.e., $L_1 = L_2 = L_3 = L_4 = L$).

Figure 13 is a diagram illustrating the effect in the frequency domain of the shifting of an 8x8 pixel upsampled sub-frame 904 according to one embodiment of the present invention. As shown in Figure 13, upsampled sub-frame 904 is shifted by shifting stage 1002 to generate shifted image 1004. Taking the FFT of upsampled sub-frame 904 results in image (L_U) 1006. Taking the FFT of shifted image 1004 results in image (L_US) 1008. Image (L_US) 1008 includes four 4x4 pixel portions, which are image portion (LS_1) 1010A, image portion (LS_2) 1010B, image portion (LS_3) 1010C, and image portion (LS_4) 1010D. As shown in Figure 13, image 1008 is the same as image 1006 multiplied by a complex exponential, W , (i.e., $L_US = W \bullet L_U$), where “ \bullet ” denotes pointwise multiplication. The values for the complex exponential, W , are given by the following Equation XV:

Equation XV

$$[W]_{(k_1, k_2)} = e^{\frac{j2\pi(k_1 + k_2)}{MN}}$$

where:

k_1 = row coordinate in the FFT domain;

k_2 = column coordinate in the FFT domain;

M = number of columns in the image; and

N = number of rows in the image.

The system 500 shown in Figure 8 can be represented mathematically in
5 an error cost function by the following Equation XVI:

Equation XVI

$$(\mathbf{L}_A^*, \mathbf{L}_B^*) = \underset{(\mathbf{L}_A, \mathbf{L}_B)}{\operatorname{argmin}} J = \underset{(\mathbf{L}_A, \mathbf{L}_B)}{\operatorname{argmin}} \sum_i [\hat{\mathbf{F}}_i(\mathbf{L}_A + \hat{\mathbf{W}}_i \mathbf{L}_B) - \mathbf{H}_i]^H [\hat{\mathbf{F}}_i(\mathbf{L}_A + \hat{\mathbf{W}}_i \mathbf{L}_B) - \mathbf{H}_i]$$

where:

- ($\mathbf{L}_A^*, \mathbf{L}_B^*$) = vectors representing the optimal FFT's of
sub-frames 30F and 30G, respectively, shown in Figure 8;
- 10 J = error cost function to be minimized;
- i = index identifying FFT blocks that are averaged (e.g.,
for image 908 in Figure 12, four blocks are averaged,
with $i=1$ corresponding to block 910A, $i=2$ corresponding
to block 910B, $i=3$ corresponding to block 910C, and $i=4$
15 corresponding to block 910D);
- \mathbf{F} = matrix representing the FFT of the interpolating filter,
 f ;
- \mathbf{L}_A = vector representing the FFT of sub-frame 30F shown
in Figure 8;
- 20 \mathbf{L}_B = vector representing the FFT of sub-frame 30G
shown in Figure 8;
- \mathbf{W} = matrix representing the FFT of the complex
coefficient given by Equation XV;
- \mathbf{H} = vector representing the FFT of the desired high
25 resolution image 28.

The superscript "H" in Equation XVI represents the Hermitian (i.e., \mathbf{X}^H is the Hermitian of \mathbf{X}). The "hat" over the letters in Equation XVI indicates that those letters represent a diagonal matrix, as defined in the following Equation XVII:

Equation XVII

$$\hat{\mathbf{X}} = \text{diag}(\mathbf{X}) = \begin{pmatrix} X_1 & 0 & 0 & 0 \\ 0 & X_2 & 0 & 0 \\ 0 & 0 & X_3 & 0 \\ 0 & 0 & 0 & X_4 \end{pmatrix}$$

Taking the derivative of Equation XVI with respect to the complex conjugate of \mathbf{L}_A and setting it equal to zero results in the following Equation

5 XVIII:

Equation XVIII

$$\frac{\partial J}{\partial \bar{\mathbf{L}}_A} = \sum_i \underbrace{\bar{\mathbf{F}}_i \hat{\mathbf{F}}_i}_{\hat{\mathbf{A}}} \mathbf{L}_A + \sum_i \underbrace{\bar{\mathbf{F}}_i \hat{\mathbf{F}}_i \hat{\mathbf{W}}_i}_{\hat{\mathbf{B}}} \mathbf{L}_B - \sum_i \underbrace{\bar{\mathbf{F}}_i \mathbf{H}_i}_{\mathbf{C}} = \mathbf{0}$$

Taking the derivative of Equation XVI with respect to the complex conjugate of \mathbf{L}_B and setting it equal to zero results in the following Equation

10 XIX:

Equation XIX

$$\frac{\partial J}{\partial \bar{\mathbf{L}}_B} = \sum_i \underbrace{\bar{\mathbf{W}}_i \bar{\mathbf{F}}_i \hat{\mathbf{F}}_i}_{\hat{\mathbf{B}}} \mathbf{L}_A + \sum_i \underbrace{\bar{\mathbf{F}}_i \hat{\mathbf{F}}_i}_{\hat{\mathbf{A}}} \mathbf{L}_B - \sum_i \underbrace{\bar{\mathbf{W}}_i \bar{\mathbf{F}}_i \mathbf{H}_i}_{\mathbf{D}} = \mathbf{0}$$

The horizontal bar over the letters in Equations XVIII and XIX indicates that those letters represent a complex conjugate (i.e., $\bar{\mathbf{A}}$ represents the complex conjugate of \mathbf{A}).

15

Solving Equations XVIII and XIX for \mathbf{L}_A and \mathbf{L}_B results in the following Equations XX and XXI

Equation XX

$$\mathbf{L}_B = (\bar{\mathbf{B}} \hat{\mathbf{A}}^{-1} \hat{\mathbf{B}})^{-1} (\mathbf{D} - \hat{\mathbf{A}}^{-1} \mathbf{C})$$

20

Equation XXI

$$\mathbf{L}_A = \hat{\mathbf{A}}^{-1}(\mathbf{C} - \hat{\mathbf{B}}\mathbf{L}_B)$$

Equations XX and XXI may be implemented in the frequency domain using pseudo-inverse filtering. In one embodiment, sub-frame generation unit
5 36 is configured to generate sub-frames 30 based on Equations XX and XXI.

VIII. Adaptive Multi-Pass

An adaptive multi-pass algorithm for generating sub-frames 30 according to one embodiment uses past errors to update estimates for the sub-frame data, and provides fast convergence and low memory requirements. The adaptive
10 multi-pass solution according to one embodiment is described in the context of the system 600 shown in Figure 9. The system 600 shown in Figure 9 can be represented mathematically in an error cost function by the following Equation XXII:

15 Equation XXII

$$J^{(n)}(\mathbf{n}) = |e^{(n)}(\mathbf{n})|^2 = \left(\sum_{\mathbf{k}} l_Q^{(n)}(\mathbf{k}) f(\mathbf{n} - \mathbf{k}) - h(\mathbf{n}) \right)^2$$

where:

n = index identifying the current iteration;

$J^{(n)}(\mathbf{n})$ = error cost function at iteration n ;

$e^{(n)}(\mathbf{n})$ = square root of the error cost function,

20 $J^{(n)}(\mathbf{n})$;

\mathbf{n} and \mathbf{k} = indices for identifying high resolution pixel locations in images 604 and 610;

$l_Q^{(n)}(\mathbf{k})$ = image data from upsampled image 604 at location \mathbf{k} ;

25 $f(\mathbf{n} - \mathbf{k})$ = filter coefficient of the interpolating filter at a position $\mathbf{n} - \mathbf{k}$; and

$h(\mathbf{n})$ = image data for desired high resolution
image 28 at location \mathbf{n} .

As can be seen from Equation XXII, rather than minimizing a global spatial domain error by summing over the entire high resolution image as shown
5 in Equation IX above, a local spatial domain error, which is a function of \mathbf{n} , is being minimized.

A least mean squares (LMS) algorithm is used in one embodiment to determine the update, which is represented in the following Equation XXIII:

Equation XXIII

$$l_Q^{(n+1)}(\mathbf{t}) = l_Q^{(n)}(\mathbf{t}) + \alpha \frac{\partial J^{(n)}(\mathbf{n})}{\partial l_Q^{(n)}(\mathbf{t})}, \quad \mathbf{t} \in \Theta$$

10

where:

Θ = the set of quincunx lattice points (i.e., the dark pixels in upsampled image 604 in Figure 9); and
 α = sharpening factor.

Taking the derivative of Equation XXII provides the value for the
15 derivative in Equation XXIII, which is given in the following Equation XXIV:

Equation XXIV

$$\frac{\partial J^{(n)}(\mathbf{n})}{\partial l_Q^{(n)}(\mathbf{t})} = 2 \left(\sum_{\mathbf{k}} l_Q^{(n)}(\mathbf{k}) f(\mathbf{n} - \mathbf{k}) - h(\mathbf{n}) \right) f(\mathbf{n} - \mathbf{t})$$

In one embodiment, a block-LMS algorithm using the average gradient over a “region of influence” is used to perform the update, as represented by the
20 following Equation XXV:

Equation XXV

$$l_Q^{(n+1)}(\mathbf{t}) = l_Q^{(n)}(\mathbf{t}) + \alpha \sum_{\mathbf{n} \in \Omega} \frac{\partial J^{(n)}(\mathbf{n})}{\partial l_Q^{(n)}(\mathbf{t})}$$

where:

Ω = region of influence

Figure 14 is a diagram illustrating regions of influence (Ω) 1106 and 1108 for pixels in an upsampled image 1100 according to one embodiment of the present invention. Pixel 1102 of image 1100 corresponds to a pixel for a first sub-frame, and pixel 1104 of image 1100 corresponds to a pixel for a second sub-frame. Region 1106, which includes a 2x2 array of pixels with pixel 1102 in the upper left corner of the 2x2 array, is the region of influence for pixel 1102. Similarly, region 1108, which includes a 2x2 array of pixels with pixel 1104 in the upper left corner of the 2x2 array, is the region of influence for pixel 1104.

Figure 15 is a diagram illustrating the generation of an initial simulated high resolution image 1208 based on an adaptive multi-pass algorithm according to one embodiment of the present invention. An initial set of low resolution sub-frames 30K-1 and 30L-1 are generated based on an original high resolution image 28. In the illustrated embodiment, the initial set of sub-frames 30K-1 and 30L-1 are generated using an embodiment of the nearest neighbor algorithm described above with reference to Figure 5. The sub-frames 30K-1 and 30L-1 are upsampled to generate upsampled image 1202. The upsampled image 1202 is convolved with an interpolating filter 1204, thereby generating a blocked image, which is then multiplied by a factor of 0.5 to generate simulated high resolution image 1208. In the illustrated embodiment, the interpolating filter 1204 is a 2x2 filter with filter coefficients of "1", and with the center of the convolution being the upper left position in the 2x2 matrix. The lower right pixel 1206 of the interpolating filter 1204 is positioned over each pixel in image 1202 to determine the blocked value for that pixel position. As shown in Figure 15, the lower right pixel 1206 of the interpolating filter 1204 is positioned over the pixel in the third row and fourth column of image 1202, which has a value of "0". The blocked value for that pixel position is determined by multiplying the filter coefficients by the pixel values within the window of the filter 1204, and adding the results. Out-of-frame values are considered to be "0". For the illustrated embodiment, the blocked value for the pixel in the third row and fourth column of image 1202 is given by the following Equation XXVI

Equation XXVI

$$(1 \times 0) + (1 \times 5) + (1 \times 5) + (1 \times 0) = 10$$

The value in Equation XXVI is then multiplied by the factor 0.5, and the result (i.e., 5) is the pixel value for the pixel 1210 in the third row and the fourth
5 column of the initial simulated high resolution image 1208.

After the initial simulated high resolution image 1208 is generated, correction data is generated. Figure 16 is a diagram illustrating the generation of correction data based on the adaptive multi-pass algorithm according to one embodiment of the present invention. As shown in Figure 16, the initial
10 simulated high resolution image 1208 is subtracted from the original high resolution image 28 to generate an error image 1302. Correction sub-frames 1312 and 1314 are generated by averaging 2x2 blocks of pixels in error image 1302. For example, the pixel 1308 in the first column and first row of error image 1302 has a region of influence 1304. The pixel values within the region
15 of influence 1304 are averaged to generate a first correction value (i.e., 0.75). The first correction value is used for the pixel in the first column and the first row of correction sub-frame 1312. Similarly, the pixel 1310 in the second column and second row of error image 1302 has a region of influence 1306. The pixel values within the region of influence 1306 are averaged to generate a
20 second correction value (i.e., 0.75). The second correction value is used for the pixel in the first column and the first row of correction sub-frame 1314.

The correction value in the first row and second column of correction sub-frame 1312 (i.e., 1.38) is generated by essentially sliding the illustrated region of influence box 1304 two columns to the right and averaging those four
25 pixels within the box 1304. The correction value in the second row and first column of correction sub-frame 1312 (i.e., 0.50) is generated by essentially sliding the illustrated region of influence box 1304 two rows down and averaging those four pixels within the box 1304. The correction value in the second row and second column of correction sub-frame 1312 (i.e., 0.75) is
30 generated by essentially sliding the illustrated region of influence box 1304 two

columns to the right and two rows down and averaging those four pixels within the box 1304.

The correction value in the first row and second column of correction sub-frame 1314 (i.e., 0.00) is generated by essentially sliding the illustrated region of influence box 1306 two columns to the right and averaging those pixels within the box 1306. Out-of-frame values are considered to be "0". The correction value in the second row and first column of correction sub-frame 1314 (i.e., 0.38) is generated by essentially sliding the illustrated region of influence box 1306 two rows down and averaging those pixels within the box 1306. The correction value in the second row and second column of correction sub-frame 1314 (i.e., 0.00) is generated by essentially sliding the illustrated region of influence box 1306 two columns to the right and two rows down and averaging those four pixels within the box 1306.

The correction sub-frames 1312 and 1314 are used to generate updated sub-frames. Figure 17 is a diagram illustrating the generation of updated sub-frames 30K-2 and 30L-2 based on the adaptive multi-pass algorithm according to one embodiment of the present invention. As shown in Figure 17, the updated sub-frame 30K-2 is generated by multiplying the correction sub-frame 1312 by the sharpening factor, α , and adding the initial sub-frame 30K-1. The updated sub-frame 30L-2 is generated by multiplying the correction sub-frame 1314 by the sharpening factor, α , and adding the initial sub-frame 30L-1. In the illustrated embodiment, the sharpening factor, α , is equal to 0.8.

In one embodiment, updated sub-frames 30K-2 and 30L-2 are used in the next iteration of the adaptive multi-pass algorithm to generate further updated sub-frames. Any desired number of iterations may be performed. After a number of iterations, the values for the sub-frames generated using the adaptive multi-pass algorithm converge to optimal values. In one embodiment, sub-frame generation unit 36 is configured to generate sub-frames 30 based on the adaptive multi-pass algorithm.

30

The embodiment of the adaptive multi-pass algorithm described above with reference to Figures 15-17 is for two-position processing. For four-position processing, Equation XXIV becomes the following Equation XXVII:

Equation XXVII

$$\frac{\partial J^{(n)}(\mathbf{n})}{\partial l^{(n)}(\mathbf{t})} = 2 \left(\sum_{\mathbf{k}} l^{(n)}(\mathbf{k}) f(\mathbf{n} - \mathbf{k}) - h(\mathbf{n}) \right) f(\mathbf{n} - \mathbf{t})$$

5

where:

$l^{(n)}$ = low resolution data for the four sub-frames
30;

And Equation XXIII becomes the following Equation XXVIII:

10

Equation XXVIII

$$l^{(n+1)}(\mathbf{t}) = l^{(n)}(\mathbf{t}) + \alpha \frac{\partial J^{(n)}(\mathbf{n})}{\partial l^{(n)}(\mathbf{t})}$$

For four-position processing, there are four sub-frames, so the amount of low resolution data is the same as the amount of high resolution data. Each high resolution grid point contributes one error, and there is no need to average gradient update as represented in Equation XXV above. Rather, the error at a given location directly gives the update.

15

As described above, in one embodiment, the adaptive multi-pass algorithm uses a least mean squares (LMS) technique to generate correction data. In another embodiment, the adaptive multi-pass algorithm uses a projection on a convex set (POCS) technique to generate correction data. The adaptive multi-pass solution based on the POCS technique according to one embodiment is described in the context of the system 600 shown in Figure 9. The system 600 shown in Figure 9 can be represented mathematically in an error cost function by the following Equation XXIX:

20

25

Equation XXIX

$$|e(\mathbf{n})| = \left| \left(\sum_{\mathbf{k}} l_Q(\mathbf{k}) f(\mathbf{n} - \mathbf{k}) - h(\mathbf{n}) \right) \right|$$

where:

$e(\mathbf{n})$ = error cost function;

\mathbf{n} and \mathbf{k} = indices identifying high resolution pixel locations;

$l_Q(\mathbf{k})$ = image data from upsampled image 604 at location \mathbf{k} ;

$f(\mathbf{n} - \mathbf{k})$ = filter coefficient of the interpolating filter at a position $\mathbf{n} - \mathbf{k}$; and

$h(\mathbf{n})$ = image data for desired high resolution image 28 at location \mathbf{n} .

A constrained set for the POCS technique is defined by the following Equation XXX:

Equation XXX

$$C(\mathbf{n}) = \left\{ l_Q(n) : \left| \left(\sum_{\mathbf{k}} l_Q(\mathbf{k}) f(\mathbf{n} - \mathbf{k}) - h(\mathbf{n}) \right) \right| \leq \eta \right\}$$

where:

$C(\mathbf{n})$ = constrained set that includes all sub-frame data from upsampled image 604 that is bounded by parameter, η ; and

η = error magnitude bound constraint.

The sub-frame pixel values for the current iteration are determined based on the following Equation XXXI:

Equation XXXI

$$l_Q^{(n+1)}(t) = \begin{cases} (1-\lambda) l_Q^{(n)}(t) + \lambda \frac{e(\mathbf{n}^*) - \eta}{\|f\|^2} & e(\mathbf{n}^*) > \eta \quad (t \in \Theta) \\ (1-\lambda) l_Q^{(n)}(t) + \lambda \frac{e(\mathbf{n}^*) + \eta}{\|f\|^2} & e(\mathbf{n}^*) < \eta \\ l_Q^{(n)}(t) & e(\mathbf{n}^*) = \eta \end{cases}$$

where:

n = index identifying the current iteration;

λ = relaxation parameter; and

$\|f\|$ = norm of the coefficients of the interpolating filter.

The symbol, \mathbf{n}^* , in Equation XXXI represents the location in the region of influence, Ω , where the error is a maximum, and is defined by the following

Equation XXXII:

Equation XXXII

$$\mathbf{n}^* = \operatorname{argmax}\{\mathbf{n} \in \Omega : |e(\mathbf{n})|\}$$

Figure 18 is a diagram illustrating the generation of correction data based on the adaptive multi-pass algorithm using a POCS technique according to one embodiment of the present invention. In one embodiment, an initial simulated high resolution image 1208 is generated in the same manner as described above with reference to Figure 15, and the initial simulated high resolution image 1208 is subtracted from the original high resolution image 28 to generate an error image 1302. The Equation XXXI above is then used to generate updated sub-frames 30K-3 and 30L-3 from the data in error image 1302. For the illustrated embodiment, it is assumed that relaxation parameter, λ , in Equation XXXI is equal to 0.5, and the error magnitude bound constraint, η , is equal to 1.

With the POCS technique, rather than averaging the pixel values within the region of influence to determine a correction value as described above with reference to Figure 16, the maximum error, $e(\mathbf{n}^*)$, within the region of influence

is identified. An updated pixel value is then generated using the appropriate formula from Equation XXXI, which will depend on whether the maximum error, $e(\mathbf{n}^*)$, within the region of influence is greater than 1, less than 1, or equal to 1 (since $\eta = 1$ for this example).

5 For example, the pixel in the first column and first row of error image 1302 has a region of influence 1304. The maximum error within this region of influence 1304 is 1 (i.e., $e(\mathbf{n}^*) = 1$). Referring to Equation XXXI, for the case where $e(\mathbf{n}^*) = 1$, the updated pixel value is equal to the previous value for this pixel. Referring to Figure 15, the previous value for the pixel in the first column
10 and the first row of sub-frame 30K-1 was 2, so this pixel remains with a value of 2 in updated sub-frame 30K-3. The pixel in the second column and second row of error image 1302 has a region of influence 1306. The maximum error within this region of influence 1306 is 1.5 (i.e., $e(\mathbf{n}^*) = 1.5$). Referring to Equation XXXI, for the case where $e(\mathbf{n}^*) > 1$, the updated pixel value is equal to half the
15 previous value for this pixel, plus half of the quantity $(e(\mathbf{n}^*) - 1)$, which is equal to 1.25. Referring to Figure 15, the previous value for the pixel in the first column and the first row of sub-frame 30L-1 was 2, so the updated value for this pixel is 1.25 in updated sub-frame 30L-3.

 The region of influence boxes 1302 and 1304 are essentially moved
20 around the error image 1302 in the same manner as described above with reference to Figure 16 to generate the remaining updated values in updated sub-frames 30K-3 and 30L-3 based on Equation XXXI.

 Although specific embodiments have been illustrated and described
herein for purposes of description of the preferred embodiment, it will be
25 appreciated by those of ordinary skill in the art that a wide variety of alternate and/or equivalent implementations may be substituted for the specific
embodiments shown and described without departing from the scope of the
present invention. Those with skill in the mechanical, electro-mechanical,
electrical, and computer arts will readily appreciate that the present invention
30 may be implemented in a very wide variety of embodiments. This application is intended to cover any adaptations or variations of the preferred embodiments

discussed herein. Therefore, it is manifestly intended that this invention be limited only by the claims and the equivalents thereof.